

eFlow3N Power Supply/Charger



• 115VAC, 60Hz, 2 amp.

• Power limited output.

Fire Alarm Disconnect:

(form "C" contacts).

Battery Backup:

• 12VDC or 24VDC selectable output.

• Auxiliary Power Limited output

• Maximum charge current 1.54 amp.

instantaneous with no interruption.

AC fail supervision (form "C" contacts).Battery fail & presence supervision

rated @ 1 amp (unswitched).Over Voltage Protection.

• 12VDC or 24VDC @ 2.5 amp supply current.

• Built-in charger for sealed lead acid or gel type batteries.

• Automatic switch over to stand-by battery when

AC fails. Transfer to stand-by battery power is

• Supervised Fire Alarm disconnect (latching or

non-latching) 10K EOL resistor. Operates on a

normally open (NO) or normally closed (NC) trigger.

<u>Overview</u>

eFlow3N is a power supply/charger which converts a 115VAC, 60Hz input into a single 12VDC or 24VDC Class 2 Rated power limited output.



Specifications

Supervision (cont'd):

 Low power shutdown. Shuts down DC output terminals if battery voltage drops below 80% of nominal. Prevents deep battery discharge.

Fuse Ratings:

- Input fuse: 5A/250V.
- Battery fuse: 3A/32V.

Visual Indicators:

- Green AC Power LED indicates 115VAC present.
- AC input and DC output LED indicators.

Additional Features:

- Short circuit and overload protection.
- Unit is complete with power supply, enclosure, battery leads and cam lock.

Mechanical:

- Enclosure Dimensions (H x W x D approx.): 13.5" (342.9mm) x 13" (330.2mm) x 3.25" (82.55mm)
 Accommodates up to two (2)12VDC/7AH batteries.
- Product weight (approx.): 8.5 lbs. (3.86 kg.).
- Shipping weight (approx.): 9.4 lbs. (4.26 kg.).

Agency Approvals



Supervision:

Input:

Output:

UL 294 UL Listed for Access Control System Units.

UL 603 UL Listed for Power Supplies for Use with Burglar-Alarms Systems.

UL 1481 UL Listed for Power Supplies for Fire Protective Signaling Systems.



ULC-S318-96 - Power Supplies for Burglar Alarm Systems. Also suitable for Access Control.

