5-Disc CD Auto Changer CM-290P



equipped with an MP3 / WMA decoder, lets you not only enjoy regular audio CDs, but also MP3 or WMA-encoded CD-R/RW discs in applications like Houses of Worship and Background Music. The DCM-290P features Denon's 5-disc changer mechanism for smooth, quiet operation.

Coaxial and Optical Digital Outputs

Headphone Jack

Specifications

Audio Section Frequency Response	2 Hz - 20 kHz
Dynamic Range	98 dB
Signal-to-Noise Ratio	108 dB
Total Harmonic Distortion	0.003%
Channel Separation	98 dB
Line Out Level	Fix 2.0V (10 k ohms/kohms
Digital Output	Coaxial / Optical
General Power Supply	AC 120 V, 60 Hz
Power Consumption	15 W
Dimensions	434 (W) x 120 (H) x 400 (D) mm
	17 3/32*(W) x 4 3/4*(H) x 15 3/4*(D)
Weight	6.3 kg, 13.1 lbs
Accessory	3U rack kit included
	IR Remote Control

Key Features CD-R/RW Playback

MP3 / WMA Decoders

The DCM-290P plays finalized CD-R/RW discs containing MP3 or WMA audio files. When they are in these formats, a single CD-R/RW disc can contain up to 10 times more tracks than an ordinary audio CD. CD-R/RW discs containing a large number of MP3 files are ideal for use in long-play applications such as background music.

Advanced Multi-Level Noise Shaping DAC

The DCM-290P features a multi-level noise shaping DAC. This multilevel modulation powerfully removes the adverse effects of jitter, and because it is built into the output amp, a clean analog output with suppressed high-frequency interference can be directly obtained.

8-Times Oversampling Digital Filter

Increasing the oversampling frequency by a factor of eight makes possible an extraordinary degree of attenuation and reduces frequency irregularities in the audio range to an absolute minimum.

Synchronized Recording Function

Full Selection of Program Playback

The DCM-290P lets you combine up to 32 tracks from the five or fewer CDs which are loaded.

3-Mode Random Playback

Full random/program random/disc sequential random

Intelligent Disc Scan

The disc skip button can rotate the carousel tray clockwise or counterclockwise when searching for a disc. (Counter-clockwise rotation is operable only by remote controller.)

20-Selection Music Calendar Display

PLEASE NOTE: Design and specifications are subject to change without notice.

D&M Professional

1100 Maplewood Drive Itasca, Illinois 60143 Tel: 630.741.0330 Fax: 630.741.0652 www.d-mpro.com

© 2006 D&M Professional. All rights reserved.

FNO

marantz

PROFESSIONAL